## Instruction Sheet Security Laptop Stand AL-78545





Culindan





1/4-20 Nat. Oty: 4 Planger - Oty: 1 Spring - Oty: 1 Spring - Oty: 1 Dual lock - Oty: 4 Dual lock - Oty: 4

Place the Base on the floor and assemble the Hub Extension, Cylinder and Upper Column Assembly



Place the Spring and Plunger into the recess in the top of the Upper Column Assembly


Uspack the cartons and check carefully to determine that all of the above components have been supplied. Note that a 7/16" wrench is required for assembly, ALCO

800-323-4282

www.alcosales.com



Loosen the locking Lever and unfold the Replacard Tray to allow access to the mounting study.



To open the cover and insert your computer, use the Security Key to turn the fasteners 1/4 turn counter-clockwise. The fastener should pop up to give a visible indication that it is unlocked. To refasten, use the key to push the fastener back into it's socket and turn clockwise until locked.



Place the Housing/Keyboard Tray Assembly onto the Upper Column Assembly. Thread the nuts onto the mounting a 7/16' wrench

Keyboard Tray Locking Lever



800-323-4282 www.alcosales.com